

Order Number

Serial Number

## PRODUCT / TEST MANUAL

**2C58K48**

## INSTANTANEOUS OVERCURRENT

<b>Issue Level</b>	<b>Date</b>	<b>Summary of changes</b>
B	12/04/1996	Initial issue.

Due to RMS continuous product improvement policy this information is subject to change without notice.

<b>Document updated</b>	<b>Checked</b>	<b>Registered</b>	<b>.pdf file created</b>	<b>.pdf uploaded to web site</b>

## 1. DESCRIPTION OF RELAY

The 2C58K48 is a triple-pole single output instantaneous overcurrent relay having less than 20ms operate and 15ms release times at 20X setting current. Heavy duty output contacts capable of breaking 0.5A at 250V DC resistive are provided. Air-cored current transformers are used to enable fast operate times to be maintained regardless of previous current offsets which may have occurred.

## 2. SPECIFICATION

Auxiliary Supply Voltage	250V DC +20% -30%
Auxiliary Supply Burden (at 250V)	<6.5W output relay dropped out <16W output relay picked up
Nominal Input Current	1A
Sensing Supply Burden (at 1A)	<0.1VA
Nominal setting Range	50%-200% continuously variable per pole
Number of Poles	3 (with common output)
Frequency Tolerance	-6% to +2% of 50Hz
Ambient Temperature Range	-5°C to 55°C
Accuracy	±5% of maximum setting
Dropout/Pickup Ratio	70 - 75% Nominal
Withstand Current (independent of setting)	10A continuous 40A for 3 seconds
Operate Time	<20ms Symmetrical or fully offset
Release Time	<15ms Symmetrical or fully offset with current interruption at a zero current crossing

### Output Relay Contact Ratings

#### **Make and Carry Continuously**

3000 VA AC resistive with maximums of 660 Volt and 12 Amp  
3000 VA DC resistive with maximums of 660 Volt and 12 Amp

#### **Make and Carry of 0.5 Second**

7500 VA AC resistive with maximums of 660 Volt and 30 Amp  
7500 VA DC resistive with maximums of 660 Volt and 30 amp

## 2. SPECIFICATION (Cont)

### AC Break Capacity

3000 VA AC resistive with maximums of 660 Volt and 12 Amp

### DC Break Capacity (Amps)

Voltage			24V	48V	125V	250V
Resistive rating		a	12	1.5	0.5	0.25
		b	12	12	10	5
L/R=40mS	Maximum break	a	12	1	0.4	0.2
		b	30	15	5.5	3.5
	1K operations (N3 Rating)	b	12	12	5	2.5

a = Without magnetic blowouts    b = With magnetic blowouts

\* As tested by Powernet Yarraville laboratories in Victoria.

## 3. TEST EQUIPMENT REQUIRED

DC Auxiliary Supply

AC Current Supply

AC Ammeter

Electronic Counter (for measuring operate and release times)

Oscilloscope

Decade Boxes

High Voltage Test Equipment

## 4. ASSOCIATED DRAWINGS

159-058-148

2C58K48 Wiring Diagram

660-093-209

Circuit Diagram Current Sensing PCB

660-093-302

Loading Diagram Current Sensing PCB

## 5. HIGH VOLTAGE TESTING

- a) Apply 2KV RMS 50 Hz between terminal groups as listed in A & B below for 1 minute.
- b) Apply 3 5KV 1/50us pulses of each polarity as listed in A & B below.

### Group A

1,2,3,4,5,6,7,8  
1,2,5,6,9,10,13,14  
1,2,3,4,9,10,11,12  
All Terminals

### Group B

9,10,11,12,13,14,19,20  
3,4,7,8,11,12,19,20  
5,6,7,8,13,14,19,20  
Frame

## 6. CALIBRATION & TEST PROCEDURE

### 6.1 Current Sensing

**Note:** The calibration of only one phase of the circuit will be described (Input A). Component reference numbers refer to 660.093.209.

- a) Adjust pot knob for equal overtravel at scale ends if necessary.
- b) Apply scale minimum current through input A (terminals 9 & 10).
- c) Connect a decade box across R1 (158.058.148 reference ) avlugs located on Motherboard 660/105-2. The value of R1 determines the value of pickup current at a particular dial setting.
- d) Apply auxiliary supply voltage of 250V DC.
- e) Check that TP"E" waveform is clean and varies by a factor of four to one in amplitude as the dial pot is moved from minimum to maximum setting. R3 may be decreased if the scale span is too small or increased if the scale span is too large.
- f) Check that TP"F" waveform is as smooth as possible (ie. symmetrical 3 phase ripple). If percentage ripple is too great C5 may be altered to achieve best symmetry.
- g) Adjust decade box so that relay just picks up at 2A for a dial setting of 2A.
- h) Check that at the 0.5A dial setting pickup occurs at this value.
- i) Replace decade box with nearest preferred value of fixed resistor and check the following scale calibration points.

MINIMUM	MAXIMUM	NOMINAL	ACTUAL	UNIT
0.42	0.58	0.5		A
0.92	1.08	1.0		A
1.42	1.58	1.5		A
1.92	2.08	2.0		A

- j) Check that hysteresis is between 70% and 75%. Repeat f) if not.

**Actual**



- c) Set input C dial to 0.5A and input C current to 10A.

PU time <19 ms @ aux. supply 185V  
DO time <14 ms @ aux. supply 290V.

	ms
	ms

## 7. GENERAL & FUNCTIONAL

- a) Check that unit operates satisfactorily over the range of 75% to 115% auxiliary supply.
- b) Check that R7 and R8 have been correctly loaded on mother board.
- c) Check that quiescent current at 250 V is 26mA +10% with output relay dropped out and 100mA with output relay picked up.
- d) Check that the relay is electrically sound and mechanically robust as per Standard Inspection & Test Schedule 903-000-026.

PASS

TESTED BY : \_\_\_\_\_ DATE : \_\_\_\_\_

## 8. CONNECTION DIAGRAM

