



Order Number

Serial Number

PRODUCT / TEST MANUAL

2C58K49

INSTANTANEOUS OVERCURRENT

Issue Level	Date	Summary of changes
A	07/04/1998	Initial issue.

Due to RMS continuous product improvement policy this information is subject to change without notice.

Document updated	Checked	Registered	.pdf file created	.pdf uploaded to web site

1. DESCRIPTION OF RELAY

The 2C58K49 is a triple-pole single output instantaneous overcurrent relay having less than 20ms operate and 15ms release times at 20X setting current. Heavy duty output contacts capable of breaking 0.25A at 250V DC resistive are provided. Air-cored current transformers are used to enable fast operate times to be maintained regardless of previous current offsets which may have occurred.

2. SPECIFICATION

Auxiliary Supply Voltage	125V DC +20% -30%
Auxiliary Supply Burden (at 250V)	<6.5W output relay dropped out <16W output relay picked up
Nominal Input Current	1A
Sensing Supply Burden (at 1A)	<0.1VA
Nominal setting Range	50%-200% continuously variable per pole
Number of Poles	3 (with common output)
Frequency Tolerance	-6% to +2% of 50Hz
Ambient Temperature Range	-5°C to 55°C
Accuracy	±5% of maximum setting
Dropout/Pickup Ratio	60% Nominal
Withstand Current (independent of setting)	5A continuous 40A for 3 seconds
Operate Time	<20ms Symmetrical or fully offset
Release Time	<15ms Symmetrical or fully offset with current interruption at a zero current crossing

159-058-949

Sheet 3 of 7

2. SPECIFICATION (Cont)

Output Relay Contact Ratings

Make and Carry Continuously

3000 VA AC resistive with maximums of 660 Volt and 12 Amp

3000 VA DC resistive with maximums of 660 Volt and 12 Amp

Make and Carry of 0.25 Second

7500 VA AC resistive with maximums of 660 Volt and 30 Amp

7500 VA DC resistive with maximums of 660 Volt and 30 amp

AC Break Capacity

3000 VA AC resistive with maximums of 660 Volt and 12 Amp

DC Break Capacity (Amps)

Voltage			24V	48V	125V	250V
Resistive rating		a	12	1.5	0.25	0.25
		b	12	12	10	5
L/R=40mS	Maximum break	a	12	1	0.4	0.2
		b	30	15	5.5	3.5
	1K operations (N3 Rating)	b	12	12	5	2.5

a = Without magnetic blowouts b = With magnetic blowouts

* As tested by Powernet Yarraville laboratories in Victoria.

3. TEST EQUIPMENT REQUIRED

DC Auxiliary Supply

AC Current Supply

AC Ammeter

Oscilloscope

Electronic Counter (for measuring operate and release times)

Decade Boxes

High Voltage Test Equipment

4. ASSOCIATED DRAWINGS

159-058-149

2C58K49 Wiring Diagram

660-093-212

Circuit Diagram Current Sensing PCB

660-093-301

Loading Diagram Current Sensing PCB

5. HIGH VOLTAGE TESTING

- a) Apply 2KV RMS 50 Hz between terminal groups as listed in A & B below for 1 minute.
- b) Apply 3 5KV 1/50us pulses of each polarity as listed in A & B below.

<u>Group A</u>	<u>Group B</u>
1,2,3,4,5,6,7,8	9,10,11,12,13,14,19,20
1,2,5,6,9,10,13,14	3,4,7,8,11,12,19,20
1,2,3,4,9,10,11,12	5,6,7,8,13,14,19,20
All Terminals	Frame

6. CALIBRATION & TEST PROCEDURE

6.1 Current Sensing

Note: The calibration of only one phase of the circuit will be described (Input A). Component reference numbers refer to 660.093.212.

- a) Adjust pot knob for equal overtravel at scale ends if necessary.
- b) Apply scale minimum current through input A (terminals 9 & 10).
- c) Connect a decade box across R1 (158.058.149 reference) avlugs located on Motherboard 660/105-2. The value of R1 determines the value of pickup current at a particular dial setting.
- d) Apply auxiliary supply voltage of 125V DC.
- e) Check that TP"E" waveform is clean and varies by a factor of four to one in amplitude as the dial pot is moved from minimum to maximum setting. R3 may be decreased if the scale span is too small or increased if the scale span is too large.
- f) Check that TP"F" waveform is as smooth as possible (ie. symmetrical 3 phase ripple). If percentage ripple is too great C5 may be altered to achieve best symmetry.
- g) Adjust decade box so that relay just picks up at 1A for a dial setting of 1A.
- h) Check that at the 0.25A dial setting pickup occurs at this value.

6. CALIBRATION & TEST PROCEDURE (Cont)



- i) Replace decade box with nearest preferred value of fixed resistor and check the following scale calibration points.

MINIMUM	MAXIMUM	NOMINAL	ACTUAL	UNIT
0.20	0.30	0.25		A
0.45	0.55	0.50		A
0.70	0.80	0.75		A
0.95	1.05	1.00		A

- j) Check that hysteresis is between 55% and 65%. Repeat f) if not.

Actual %

- k) Repeat steps a) to i) for Input B:

Ref b) Terminals 19 & 20 c) R2
e) TP"C", R21 f) TP"D", C15

Minimum	Maximum	Nominal	Actual	Unit
0.20	0.30	0.25		A
0.45	0.55	0.50		A
0.70	0.80	0.75		A
0.95	1.05	1.00		A

- l) Check that hysteresis is between 55% and 65%. Repeat f) if not .

Actual %

- m) Repeat steps a) to i) for input C:

Ref b) Terminals 11 & 12 c) R3
e) TP"A", R39 f) TP"B", C25

Minimum	Maximum	Nominal	Actual	Unit
0.20	0.30	0.25		A
0.45	0.55	0.50		A
0.70	0.80	0.75		A
0.95	1.05	1.00		A

- n) Check that hysteresis is between 55% and 65%. Repeat f) if not.

Actual %

6.2 Operate Time Check

- a) Set input A dial to 0.25A and input A current to 5A.

PU time <19 ms @ aux. supply 87.5V	<input type="text"/>	ms
DO time <14 ms @ aux. supply 150V.	<input type="text"/>	ms

- b) Set input B dial to 0.25A and input B current to 5A.

PU time <19 ms @ aux. supply 87.5V	<input type="text"/>	ms
DO time <14 ms @ aux. supply 150V.	<input type="text"/>	ms

- c) Set input C dial to 0.25A and input C current to 5A.

PU time <19 ms @ aux. supply 87.5V	<input type="text"/>	ms
DO time <14 ms @ aux. supply 150V.	<input type="text"/>	ms

7. GENERAL & FUNCTIONAL

- a) Check that unit operates satisfactorily over the range of 70% to 120% auxiliary supply.
- b) Check that R7 and R8 have been correctly loaded on mother board.
- c) Check that quiescent current at 125 V is 26mA +10% with output relay dropped out and 100mA with output relay picked up.
- d) Check that the relay is electrically sound and mechanically robust as per Standard Inspection & Test Schedule 903-000-026.

PASS

TESTED BY : _____ DATE : _____

8. CONNECTION DIAGRAM

