

Order Number

Serial Number

## PRODUCT / TEST MANUAL

**2C58K57**

**INSTANTANEOUS OVERCURRENT**

Issue Level	Date	Summary of changes
A	31/07/03	Initial issue.

Due to RMS continuous product improvement policy this information is subject to change without notice.  
This document is uncontrolled and subject to copyright.

Author	Checked & Registered	.pdf file created	Released
ERL	DG	DG	

## 1. DESCRIPTION OF RELAY

The 2C58K57 is a triple-pole single output instantaneous over current relay having less than 20ms operate and 15ms release times at 20X setting current. Heavy-duty output contacts capable of breaking 0.5A at 125V DC resistive are provided. Air-cored current transformers are used to enable fast operate times to be maintained regardless of previous current offsets which may have occurred.

## 2. SPECIFICATION

Auxiliary Supply Voltage	125V DC +20% -25%
Auxiliary Supply Burden (at 110V)	<4W output relay dropped out <15W output relay picked up
Nominal Input Current	1A
Sensing Supply Burden (at 1A)	<0.1VA
Nominal Setting Range	20% - 200% continuously variable
Number of Poles	3 (with common output)
Frequency Tolerance	-6% to +2% of 50Hz
Ambient Temperature Range	-5°C to 55°C
Accuracy	±5% of maximum setting
Dropout/Pickup Ratio	Not less than 85%
Withstand Current (independent of setting)	10A continuous 40A for 3 seconds
Operate Time	<20ms Symmetrical or fully offset
Release Time	<15ms Symmetrical or fully offset with current interruption at a zero current crossing

### Output Relay Contact Ratings

#### **Make and Carry Continuously**

3000 VA AC resistive with maximums of 660 Volt and 12 Amp  
3000 VA DC resistive with maximums of 660 Volt and 12 Amp

#### **Make and Carry of 0.5 Second**

7500 VA AC resistive with maximums of 660 Volt and 30 Amp  
7500 VA DC resistive with maximums of 660 Volt and 30 amp

## 2. SPECIFICATION (Cont)

### AC Break Capacity

3000 VA AC resistive with maximums of 660 Volt and 12 Amp

### DC Break Capacity (Amps)

Voltage			24V	48V	125 V	250V
Resistive rating		a b	12 12	1.5 12	0.5 10	0.25 5
L/R=40 mS	Maximum break	a b	12 30	1 15	0.4 5.5	0.2 3.5
	1K operations (N3 Rating)	b	12	12	5	2.5

**a = Without magnetic blowouts b = With magnetic blowouts**

\* As tested by Powernet Yarraville laboratories in Victoria.

## 3. TEST EQUIPMENT REQUIRED

DC Auxiliary Supply  
 AC Current Supply  
 AC Ammeter  
 Electronic Counter (for measuring operate and release times)  
 Oscilloscope  
 Decade Boxes  
 High Voltage Test Equipment

## 4. ASSOCIATED DRAWINGS

For energyAustralia only

This Product Test Manual is in reference to TfA 174581 Issue A 2/08/99

159-058-157	2C58K57 Wiring Diagram
660-309-201	Circuit Diagram Current Sensing PCB
660-309-301	Loading Diagram Current Sensing PCB

## 5. HIGH VOLTAGE TESTING

- a) Apply 2KV RMS 50 Hz between terminal groups as listed in A & B below for 1 minute.
- b) Apply 5KV 1/50us pulses of each polarity as listed in A & B below.

### Group A

1,2,9,10,11,12,19,20  
 3,4,7,8,9,10,11,12  
 5,6,7,8,19,20  
 All

### Group B

3,4,5,6,7,8,13,14  
 1,2,5,6,13,14,19,20  
 1,2,3,4,11,12,13,14  
 Frame

**6. CALIBRATION & TEST PROCEDURE**

**6.1 Current Sensing**

**Note:** The calibration of only one phase of the circuit will be described (Input A). Component reference numbers refer to 660.309.201

- a) Adjust pot knob for equal overtravel at scale ends if necessary.
- b) Apply scale minimum current through input A (terminals 9 & 10)
- c) Connect a decade box across R1 (158.058.157 reference) TP01-H & TP01-J on Motherboard 660/105-1. The value of R1 determines the value of pickup current at a particular dial setting.
- d) Apply auxiliary supply voltage of 125V DC
- e) Check that the following voltages appear on the test points indicated. TP01-A –125VDC, TP01-D – 0 VDC, TP01-B- 24VDC, TP01-C- 12 VDC
- f) Check that TP"E" waveform is clean and varies by a factor of four to one in amplitude as the dial pot is moved from minimum to maximum setting. R3 may be decreased if the scale span is too small or increased if the scale span is too large.
- g) Check that TP"F" waveform is as smooth as possible (ie. symmetrical 3 phase ripple). If percentage ripple is too great C5 may be altered to achieve best symmetry.
- h) Adjust decade box so that relay just picks up at 2 A for a dial setting of 2 A.
- i) Check that at the 0.5A dial setting pickup occurs at this value.
- j) Replace decade box with nearest preferred value of fixed resistor and check the following scale calibration points.

MINIMUM	MAXIMUM	NOMINAL	ACTUAL	UNIT
0.42	0.58	0.5	<input type="text"/>	A
0.92	1.08	1.0	<input type="text"/>	A
1.42	1.58	1.5	<input type="text"/>	A
1.92	2.08	2.0	<input type="text"/>	A

- k) Check that Hysteresis is not less than 85% at the above settings Repeat f) if not.

**Actual**  %

### 6.1 Current Sensing (Cont)

- l) Repeat steps a) to i) for Input B:  
 Ref b) Terminals 19 & 20  
 e) TP "C", R21

- c) R2 (TP01-G & TP01-K)  
 f) TP"D", C15

Minimum	Maximum	Nominal	Actual	Unit
0.42	0.58	0.5	<input type="text"/>	A
0.92	1.08	1.0	<input type="text"/>	A
1.42	1.58	1.5	<input type="text"/>	A
1.92	2.08	2.0	<input type="text"/>	A

- m) Check that Hysteresis is not less than 85% at the above settings Repeat f) if not.

**Actual**  %

- n) Repeat steps a) to i) for input C:  
 Ref b) Terminals 11 & 12  
 e) TP "A", R39

- c) R3 (TP01-I & TP01-L)  
 f) TP"B" C25

Minimum	Maximum	Nominal	Actual	Unit
0.42	0.58	0.5	<input type="text"/>	A
0.92	1.08	1.0	<input type="text"/>	A
1.42	1.58	1.5	<input type="text"/>	A
1.92	2.08	2.0	<input type="text"/>	A

- o) Check that hysteresis is not less than 85% at the above settings. Repeat f) if not.

**Actual**  %

### 6.2 Operate Time Check

The following tests are to be done on both min & max scale settings for each phase. Tolerance is +/- 2 mS. Pick up and drop out to be less than 20 ms

		Pick up			Drop out		
Input	Setting	Phase A	Phase B	Phase C	Phase A	Phase B	Phase C
1.0 Amp	.5						
4 Amp	2						
5.0 Amp	.5						
10.0 Amp	2						

**6.2 Operate Time Check (Cont)**

- a) Apply 10 Amp to each input in turn apply nominal auxiliary volts and ensure that the pick up is less than 20 ms from application of DC.

Setting	Phase A	Phase B	Phase C
0.5			
2.0			

- b) Apply 10 Amp to each phase in turn and remove the auxiliary DC volts, ensure that the dropout time is less than 20 mS from removal of the DC

Setting	Phase A	Phase B	Phase C
0.5			
2.0			

**7. GENERAL & FUNCTIONAL**

- a) Check that unit operates satisfactorily over the range of 93.75 volts to 150 volts auxiliary supply.
- b) Check that R7 and R8 have been correctly loaded on motherboard.
- c) Check that quiescent current at 125 V is <35mA +10% with output relay dropped out and <170mA with output relay picked up.
- d) Check that the relay is electrically sound and mechanically robust as per Standard Inspection & Test Schedule 903-000-026.

PASS

TESTED BY : \_\_\_\_\_ DATE : \_\_\_\_\_

8. CONNECTION DIAGRAM

