

Order Number

Serial Number

PRODUCT / TEST MANUAL

2T103K6

DIGITAL TIMER

Issue Level	Date	Summary of changes
A	14/12/99	Initial issue.

Due to RMS continuous product improvement policy this information is subject to change without notice.
This document is uncontrolled and subject to copyright.

Author	Checked & Registered	.pdf file created	Released
ERL	MW	MW	

1. BROAD DESCRIPTION

The 2T103 time delay on energisation relay is particularly suitable for use in protection and control schemes where precision time delays are required.

A crystal oscillator and digital dividing circuit are employed to provide the timebase for a pre-settable down counter chain. When positive supply is applied to the control input, the down counter is loaded with the thumbwheel switch setting and begins counting down. When zero is detected, the output relay picks up and the down counter stops. The three time ranges can be selected via a front panel switch which changes the divide ratio of the timebase circuit. Front panel LED's indicate the relay status.

2. SPECIFICATIONS

INITIATE INPUT 110 Volts DC
 Energise initiate input to actuate timer functions

ACCURACY The setting and repeat accuracy is:
 $\pm 0.5\%$ of setting (plus the inherent minimum time).

AUXILIARY SUPPLY 40 - 300 V DC Switch mode power supply
RESET TIME Electronic reset time is between 20 and 50 millisecond.
 Output relay dropout time is less than 20 milliseconds and removal of auxiliary supply will reset the relay in this time.

INSULATION WITHSTAND In accordance with AS2481-1981 (clause 5-4), IEC 255-5: 2KV RMS between input and frame, output and frame, and output and input. 1.2/50 5KV impulse between each terminal and earth, between circuits not normally connected together and between terminals of the same circuit.

NOISE IMMUNITY Withstands the high frequency interference test detailed in AS2481-1981 (clause 5-5 App. D), IEC 255-22-1.

STANDARD OUTPUT CONTACTS The output relay is fitted with 2 N/O + 2 N/C self-reset contacts as standard.

STANDARD OUTPUT RELAY CONTACT RATINGS
Make & Carry Continuously

1,700 VA AC resistive with maximums of 380V & 8A

1,700 VA DC resistive with maximums of 250V & 8A

Maximum Contact Capacity (Amps)

	DC			AC		
	30	125	250	110	220	250
Voltage	30	125	250	110	220	250
Resistive	10	2.4	1.2	10	7	6.6
Inductive L/R 7 ms	7.5	1.8	.9	7.5	5	4.4

OPERATION INDICATOR The standard relay has a hand resettable magnetic disc (permanent memory) indicator fitted to give visual indication that the output relay element has operated..

3. TEST EQUIPMENT REQUIRED

DC Auxiliary Supply	Frequency Counter
Digital Voltmeter	Oscilloscope
Electronic Counter (for measuring operate times)	High Voltage Test Equipment

4. ASSOCIATED DRAWINGS

164-103-001	Descriptive Manual
164-103-106	Wiring Diagram
660-307-201	Circuit Diagram
660-307-301	Loading Diagram

5. HIGH VOLTAGE TESTING

- a) Apply 2KV RMS 50 Hz between terminal groups 1 and 2 in Table 1 for 1 minute.
- b) Apply 3 5KV 1/50us pulses of each polarity between terminal groups 1 and 2 in Table 1.

TABLE 1

Group 1	Group 2
All terminals	Frame
Inputs	Outputs

6. CALIBRATION & TEST PROCEDURE

- a) Connect timing apparatus to measure interval between energisation of the initiate input and output relay contact closure. Set JO5 jumper N/O (Pins 1 & 2)
- b) Set range switch to range A and time to 000.
- c) Record pick-up time for auxiliary voltage of 40 V.

Maximum	Actual	Unit
30	<input style="width: 100px; height: 15px;" type="text"/>	ms

- d) Record drop-out time for auxiliary voltage of 300 V

Maximum	Actual	Unit
30	<input style="width: 100px; height: 15px;" type="text"/>	ms

- e) Record times for the following settings (range A)

Setting	Minimum	Maximum	Nominal	Actual	Unit
111	121	135	123	<input style="width: 100px; height: 15px;" type="text"/>	ms
222	232	245	234	<input style="width: 100px; height: 15px;" type="text"/>	ms
444	454	468	456	<input style="width: 100px; height: 15px;" type="text"/>	ms
888	898	912	900	<input style="width: 100px; height: 15px;" type="text"/>	ms

6. CALIBRATION & TEST PROCEDURE (Cont)

f) Set time to 100 and set range to B.

Minimum	Maximum	Nominal	Actual	Unit
1.01	1.02	1.01	<input type="text"/>	s

g) Set range switch to C and record pick-up time.

Minimum	Maximum	Nominal	Actual	Unit
10.01	10.02	10.01	<input type="text"/>	s

7. GENERAL & FUNCTIONAL

a) Check for correct operation of magnetic disc flag.

OK

b) Check operation of the relay fail alarm

OK

c) Check that the Time initiate functions at 110 +/- 10% VDC

OK

b) Check that the relay is electrically sound and mechanically robust as per Standard Inspection & Test Schedule 903-000-026.

PASS

TESTED BY : _____ DATE : _____

8. CONNECTION DIAGRAM

